

### Part number list

WG128128I-□□□-□□#

### Pin Assignment

Pin No.	Symbol	Description
1	DB0	Data bus line
2	DB1	Data bus line
3	DB2	Data bus line
4	DB3	Data bus line
5	DB4	Data bus line
6	DB5	Data bus line
7	DB6	Data bus line
8	DB7	Data bus line
9	C/D	Data/ Instruction select signal
10	/RD	Data read. Read data from LCD Controller
11	/WR	Data write. Write data into LCD Controller
12	/CE	Enable signal
13	/RST	Controller reset signal, Active Low
14	V <sub>O</sub>	Contrast Adjustment
15	V <sub>DD</sub>	Power supply for logic
16	V <sub>SS</sub>	Ground
17	V <sub>EE</sub>	Negative Voltage Output
18	NC/FS	No connection
19	A	Power supply for B/L +
20	K	Power supply for B/L -

### Feature

1. Built-in controller RA6963 or equivalent
2. Built-in oscillation
3. +5V single power supply
4. 8080 interface
5. (Option) Built-in Negative voltage

### Mechanical Data

Item	Standard Value	Unit
Module Dimension	72.5 x 69.9	mm
Active Area	44.77 x 44.77	mm
Mounting Hole	67.4 x 64.9	mm
Dot Pitch	0.35 x 0.35	mm
Dot Size	0.32 x 0.32	mm

### Electrical Characteristics

Item	Symbol	Standard Value	Unit
		typ.	
Input Voltage	V <sub>DD</sub>	5.0	V

### Mechanical Drawing

